ASKO MOTOR LIMITED 思科電機有限公司




AK-FF-030SA

Typical Applications :

Toy / Massager / Radio Control Car / Vacumm Cleaner
Motorized Toy / Household Appliances / Cookie Maker

机械尺寸/ Mechanical Dimensions

DIRECTION OF ROTATION



电气性能/ Electrical performance

MODEL	VOLTAGE	NO LOAD		AT MAXIMUM EFFICIENCY					STALL	
	NOMINAL	SPEED	CURRENT	SPEED	CURRENT	TOROUE	OUTPUT	EFF	TOROUE	CURRENT
		r/min	A	r/min	A	g-cm	W	%	g-cm	A
AK-FF-030SA-08300	3.0V CONSTANT	4700	0.04	2600	0.12	4	0.11	30.5	6	0.2
AK-FF-030SA-10200	6.0V CONSTANT	12800	0.043	10750	0.16	5	0.55	57.3	30	0.9
AK-FF-030SA-09210	5.0V CONSTANT	10200	0.05	7500	0.16	4.5	0.35	43.3	17	0.47
AK-FF-030SA-11155	3.0V CONSTANT	9200	0.07	7350	0.18	2.5	0.18	34.9	12	0.62